

User Guide

General Technical Specifications

Some general technical specifications of i380 module are given below

Input	230VAc \pm 15%, 50Hz
Communication	Wi-Fi 2.4GHz 802.11b/g/n
Wi-Fi signal strength	-60 dBm (min)
Internet speed	512Kbps (min)
Data Consumption	<3MB/Month (100 operations/day)
Power Consumption	0.6W idle and <5W (On Full Load)
Operating Temperature	-10° to +70°C Non-condense
Size (L x W x H)	128mm x 58mm x 25mm (3 x 8 Gang Box)
Weight	150g
Load-Wise Maximum Connection Capacity	
Each Load	200 Watt

Note: Make sure the load connected to the switch is within the switch's maximum load capacity. Also, do not install the switch in a damp or humid environment. Do not expose it to extreme temperatures.

We hope you find this user manual helpful. If you have any questions or concerns, please don't hesitate to contact our customer support team.

User Guide

Installation:

1. Turn off the power supply to the switchboard you want to install the switch on.
2. Remove the existing switch from the switchboard.
3. Connect the wires from the switchboard to the corresponding terminals on the smart WiFi switch. Make sure to follow the wiring diagram provided with the switch.
4. Screw the switch into the switchboard.
5. Turn on the power supply to the switchboard.

Configuration:

1. Download and install the “Valuecon Smart” app on your smartphone from Playstore.
2. Create an account on the app.

- a) Use Google Login, and select a Google Account; or
- b) Sign up using by entering an email ID and the desired password, and authenticate using OTP received by Email. Don't forget to check the spam folder

3. Click On Add Device, and Select i380 from the list of devices
4. Select the SSID of your WiFi network from the drop down menu and enter the password.
5. Select the device ID that appears on the next screen. It should look something like this

VCAUTO_209_15E330

Connect

6. Select the Room or Enter a new Room, once the device is successfully configured
1. Viola! Your Device is ready to use Usage: Use the app to turn the switch on or off remotely.
 2. Schedule the switch to turn on or off automatically at a specific time.
 3. Use voice commands with Amazon Alexa or Google Assistant to control the switch hands-free.
 4. Control the regulated fan using the app or voice commands, and adjust the speed as per your requirement.

Note:

- The UI can change and so can the steps. It is recommended to watch the video using the QR code for update user Guide .
- Please Watch the User Guide Video for updated Alexa and Google Home Integration.



VALUECON[®]
VALUE TO CONSUMERS



Scan For
Installation &
User Guide



Scan To Download
The App

VALUECON PRIVATE LIMITED

+91 9821003728 ✉ care@valueconsmart.com

User Guide

Standard Warranty Terms and Conditions for i380 Smart Switchboard

1. **Warranty Coverage:** The i380 Smart Switchboard is covered by a limited warranty for a period of 2 years from the date of purchase against manufacturing defects only. This warranty is valid only for products sold in India.
2. **Warranty Claim Process:** In the event of a defect, the buyer must notify Valuecon Private Limited in writing by sending an email to support@valueconsmart.com or by calling the toll-free number mentioned on the product packaging. The buyer will be required to provide the proof of purchase along with a detailed description of the issue faced with the product.
3. **Service Center Location:** The buyer will have to send the product to the official service center located in Gautam Buddha Nagar, Uttar Pradesh. The shipping cost to and from the service center will be borne by the buyer.
4. **Repair or Replacement:** Upon receipt of the product, Valuecon Private Limited will inspect the product to determine the cause of the defect. If the defect is due to a manufacturing defect and is covered by this warranty, Valuecon Private Limited will either repair or replace the product at their discretion within 30 days of receipt of the product.
5. **Exclusions:** This warranty does not cover any physical damage to the product, damage due to misuse or abuse of the product, damage due to non-compliance with the user manual, or any damage caused by application of any appliance, mobile phone, light or fixture higher than the prescribed voltage/current/amp for each output.
6. **Dispute Resolution:** All disputes arising out of or in connection with this warranty shall be subject to the exclusive jurisdiction of the courts in Delhi only.

By using the i380 Smart Switchboard, the buyer agrees to be bound by the terms and conditions of this warranty. This warranty is in lieu of all other warranties, express or implied, including any warranties of merchantability or fitness for a particular purpose. Valuecon Private Limited's liability under this warranty shall be limited to the repair or replacement of the product as provided herein.